

SERVICE BULLETIN







No. : 0IVL20040003

Date : 2004-06-15

Model	Factory	Factory Model	Suffix	Model No.	Factory	Factory Model	Suffix	Model No.
	EKHQ	MW-30LZ10	AALZKZ	L30W26	EKHQ	MW-30LZ10	ACLLKC	MW-30LZ10
	EKHQ	MW-30LZ10	AWPLKZ	MW-30LZ10				
Buyer	Buyer Name	Buyer Code	Buyer Name	Buyer Code	Buyer Name	Buyer Code		
	LGEUS	US000001	LGEAI	US000002	ZENITH	US007515		
EFFECTIVE DATE	2004-06-15		EFFECTIVE FROM(SERIAL NO.)			june 2004		
Subject	To repair image spread							
No.	Loc No.	Before Change		After Change		Note	K-Code	Remark
		Part No	DESC./SPEC.	Part No	DESC./SPEC.			
Reason Of Change								
<p>To repair an image spread problem, please perform the following:</p> <p>1) On the main board, check solder condition of R752~R761 (P/N:0RH0222D622) & P005B (6602T11001A). Perform re-soldering if necessary.</p> <p>2) Check P005B and Link cable (P/N:6631V00006Q) connection.</p> <p>3) Change Link cable (P/N:6631V00006Q).</p> <p>4) Check Link cable (P/N:6631V00006Q) and LCD Module connection.</p> <p>5) Check solder condition of wafer (Circuit No.:CN5)'s and perform re-soldering on T-con Board on the LCD Module.</p>								

**** FILE THIS SERVICE BULLETIN WITH YOUR SERVICE MANUAL**

NOTE(**) : INTERCHANGEABILITY CODE				KEY-WORD CODE	
	Parts	Set			
A	Original	Early		Original or new parts may be used in early or late production sets. Use original parts until exhausted, then stock new parts.	1. To improve performance 2. To improve productivity
	New	Late			
B	Original	Early		Original parts may be used in early production sets only. New parts may be used in early or late production sets. Use original parts where possible, then stock new parts.	3. To improve reliability 4. Change of material or dimension
	New	Late			
C	Original	Early		New parts only may be used in early or late production sets. Stock new parts.	5. Addition 6. Deletion
	New	Late			
D	Original	Early		Original parts only may be used in early production sets. New parts may be used in late production sets only. Stock original and new parts.	7. Correction
	New	Late			

CHIEF ENGINEER , *approved*
 Factory.